

## KOP602

### Programmable battery charger

#### MAIN FEATURES

- For Lead-acid, NiZn, NiCd, NiMH and lithium batteries
- Fully automatic operation
- Completely programmable
- Up to five charging phases
- Simple to use and program
- Battery monitor and Ah counter
- High precision
- Low noise
- Battery status LED indicators
- Battery temperature compensation



#### TECHNICAL CHARACTERISTICS

■ Nominal battery voltage	24V	36V	48V
■ Max. output voltage	33V	49,5V	66V
■ Nominal output current	17A	12A	9A
■ Efficiency	87%	88%	88%
■ Peak input current		4,3A	
■ Input voltage	230V $\pm$ 15% 50-60Hz		
■ Dimensions (L x W x H)	244 x 140 x 85mm		
■ Weight	2,2kg		



[www.piktronik.com](http://www.piktronik.com)